

4 Way Splitter for Foxtel SMS Systems Max 30V 2A Power Pass All Ports 17MM-DM04S-2A



For the Best

Features and Benefits

- » Foxtel approved (F31040)
- » High isolation Splitter for Foxtel SMS systems
- » Max 2A 30V DC pass all ports bidirectional
- » Return Loss $\geq 10\text{dB}$
- » Frequency range 5-2400MHz
- » Insertion loss 3.6dB to 5.8dB from 45-2400MHz



Splitters and Taps

Matchmaster has a premium range of RF Splitters & Taps ranging from 1 Way through to 8 Way. We cater for both Terrestrial and Satellite frequencies with both Single Port AC/DC and All Port DC Power Pass products available.



17MM-DM04S-2A Specifications

	Frequency	
Insertion Loss	5-40MHz	8.7dB
	40-470MHz	8.0dB
	470-1000MHz	8.0 to 9.0dB
	1000-1750MHz	9.0 to 9.5dB
	1750-2150MHz	9.5 to 10.5dB
	2150-2300MHz	10.5 to 11.5dB
Return Loss	2300-2400MHz	11.5 to 12.5dB
	5-40MHz	$\geq 10\text{dB}$
	40-470MHz	$\geq 10\text{dB}$
	470-1000MHz	$\geq 10\text{dB}$
	1000-1750MHz	$\geq 10\text{dB}$
	1750-2150MHz	$\geq 10\text{dB}$
Isolation	2150-2300MHz	$\geq 10\text{dB}$
	2300-2400MHz	$\geq 10\text{dB}$
	5-40MHz	$\geq 23\text{dB}$
	40-1000MHz	$\geq 23\text{dB}$
DC Power Passing	1000-1750MHz	$\geq 23\text{dB}$
	1750-2400MHz	$\geq 23\text{dB}$
	output/input to input/output	Max. 2A